




Light indicating voice messages received or callback requests

Preprogrammed keys

-  Cancel an enquiry call.
-  Access the various mail services.
-  Automatically redial the last number dialed.
-  To reduce receiver or ringer volume.
-  Switching between two calls (Broker call).
-  Divert your calls to another terminal.
-  To activate ringer.
-  To increase receiver or ringer volume.

Installing the programmable key label

A printed label is supplied with the terminal. This should be installed beneath the programmable keys.



1. Insert a flat "blade" into the slot (1 slot per key block).
2. Raise the cover.
3. Slide the printed label into position.
4. Replace the cover.

Using your telephone

Making a call

-  lift the receiver
-  dial directly the number for your call



To make an external call, dial the outside line access code before dialling your correspondent's number.

Receiving a call



lift the receiver

Redialling



lift the receiver



redial

Making a call-back request

your correspondent does not reply or is busy



"call-back request" function code



hang up

Directory

Programming your personal directory

Your directory can contain up to 12 numbers.



"personal directory programming" function code



numeric key on which you want to programme the number



internal or outside number to be entered



apply your choice



Calling from your personal directory



lift the receiver



"call from personal directory" function code



press programmed key

Guarantee and clauses

We, **Alcatel Business Systems**, hereby declare that we assume

Digital terminal IDS 110 (Alcatel Reflexes 4004)

product to be compliant with the essential requirements of Directive 1999/5/CE of the European Parliament and Council.

Any unauthorised modification to the product shall render this declaration of compliance null and void. A copy of the original of this declaration of compliance can be obtained by post from:

ALCATEL BUSINESS SYSTEMS
 Technical Services - Approvals Manager
 1, route du Dr. Albert Schweitzer
 F 67408 Illkirch - France



Divert your calls to another number

Divert your calls to another number



number to be called

hang up

Diverting your calls to your voice message service



code of type of forward

recorded message no.

hang up

During a conversation

Sending DTMF signals

During a conversation you sometimes have to send DTMF signals, such as with a voice server, an automated attendant or a remotely consulted answering machine. The function is automatically cancelled when you hang up.

during a conversation



dial the code for the "DTMF end to end dialling" function.

Calling a second person during a conversation

During a conversation, to call a second person.



the first call is on hold



dial

cancel second call

Receiving a second call

During a conversation, another person is trying to call you.



the first call is on hold

code for function "consultation of call on hold"

Switching between two calls (Broker call)

During a conversation, a second call is on hold. To accept the second call:



the first call is on hold

broker call

Transferring a call

During a conversation, to transfer the call to another number:



number to be called

hang up

Three-way conference

During a conversation, a second call is on hold



code for function "conference"

Use the same procedure to cancel the conference and recover the first call.

Voice message service

Consulting your voice mailbox

The light indicates that messages have been received.



follow the instructions of the voice guide

lift the receiver

Customize your terminal

Programming your personal code

This password controls access to the programming and terminal locking functions by the user (default password: 0000).



code of the "change personal code" function

enter the old password

enter the new password (twice)

Adjusting the audio functions

Terminal idle:



OR



choose the tune (16)

adjusting the ringer volume



apply your choice

Personal notes